

User manual AXIWI AT-350

In order to set up the AXIWI communication system, you have to make the following installation steps.

Before you start, first plug in the headsets.

Start with AXIWI

First you have to set up 1 unit as a "Master" unit and all other AXIWI's has to be set up as "Follower". Each random individual unit can be set up as 'Master' or can be set up as 'Follower'.

Set up as 'Master'

1. Push the **volume 'up' (+)** button.
2. display indicates the channel. And the 'M' (of Master) on the left upper side on the display indicates the Master mode.

Set up as 'Follower'

1. Push the **'on /off' button** (at least 2 seconds).
2. The number on the display indicates the channel.

If you connected the headsets to the enabled AXIWI's, you can use the Master for speaking and the Follower for listening. Each AXIWI, set as 'Follower', can activate the speaking function (next step) with a maximum of 5 speakers at the same time (excluding the Master).

Turn on the speaking function

1. Push the **'Speaking' button** shortly.
2. After pushing the 'Speaking' button a Microphone icon will appear in the display. If this is the case, the unit can talk to all other units on the same channel. You will also hear a voice saying, 'Talk on'.

Deactivate the speaking function

1. Push the **'Speaking' button** shortly.
2. After pushing the 'Speaking' button the Microphone icon will disappear in the display. The unit is back in the 'listen only' mode. At this point you will only be able to listen to the other units which have activated their speaking function. You will also hear a voice saying, 'Talk off'.

Change the channel

When the AXIWI is 'on' (as a Master or Follower) you can change the channel:

1. Press the 'Mode' (M) button briefly.
2. Change the channel with the volume buttons.
3. Confirm with the 'Mode' button.

Charging AXIWI unit

1. The unit can be recharged by a USB-to-micro-USB cable. Plug the USB micro jack into the jack plug above the volume -up button. The light at the top (next to the antenna) will light up red.
2. When the light at the top lights up green, recharging is complete, and it is advised to stop charging and to disconnect the unit from the charger. It takes about 2 hours to recharge an empty (battery) unit.

